

CPA 800 DUAL WIRELESS SYSTEM

RECEIVER

- * Operating frequency: 470-786MHz
- * Channels: 4*100channels
- * Bandwidth: 50MHz
- * Channel space: 250KHz
- * ACR/IR SYNC and scan technology
- * Battery display on LCD
- * S/N ratio: > 105dB
- * T.H.D distortion: <0.5%
- * Frequency response: 20Hz-18KHz
- * distance: 50-80 meters approx

TRANSMITTER

- * Channels: 200channels
- * Bandwidth: 50MHz
- * Channel space: 250KHz
- * Frequency stability: 0.005%
- * FM Max frequency adjusting: 45KHz
- * RF output: HIGH 10mW / LOW 5mW
- * Power supply: 2*AA batteries

